

# LogiLink®

## Universal Power Adapter 3–12 V

8 Changeable Tips Included

Art. No.: PA0198




Ideal as a replacement or secondary power adapter for electronics and small home appliance.

### Features:

- » Provide different charger adapters for easily charging most of the digital devices
- » Reliable replacement or secondary power adapter in home or office
- » Extra USB port allows you to charge another 5 V device such as mobile phone at the same time
- » Built-in protection against overcurrent, overvoltage, over-temperature and short-circuit



Home/Office



For digital camera, battery chargers, mobile phone, router, games console and many others

### Specification:

Input Voltage	AC 100–240 V 50/60 Hz 1 A max.
Output Power	DC: 3 V/4.5 V/5 V/6 V/7.5 V/9 V/ 12 V 2 A (24 W max.) USB: 5 V/1 A (5 W max.)
Efficiency	>82%
Standby Power Loss	≤0.5 W
Operating Temperature	0–45°C
Operating Humidity	10–80% RH (no condensation)
Dimensions	8.5 x 5 x 4.1 cm (without cable)
Weight	0.135 kg
Cable Length	1.45 m
DC Plug	5.5 x 2.1 mm



C	5.5 x 2.5mm
E	5.5 x 2.1mm
H	3.5 x 1.35mm
G	4.0 x 1.7mm
L	3.0 x 1.1mm
H	2.5 x 0.7mm
S	Micro USB
LED Terminal	



\*The specifications and pictures are subject to change without prior notice.  
\*All trade names referenced are the registered trademarks of their respective owners.



PA0198



4 052792 052893

Made in China

### Package Contents:

- » 1 x Universal Power Adapter
- » 8 x Changeable Tips
- » 1 x Key
- » 1 x User Manual

### Package Information:

- » Packing Dimension: 176 x 127.5 x 42 mm
- » Packing Weight: 0.22 kg
- » Carton Dimension: 505 x 372 x 285 mm
- » Carton Q'ty: 40 pcs
- » Carton Weight: 10 kg



### Warning

- \*For use with Information Technology Equipment.
- \*Compare the specifications of your device with the specifications of the adapter. The power current (A) of your device should be equal to or lower than the power current of the power supply.
- \*Only to be used indoor.
- \*Only to be used after powering on.
- \*Only to be used within max load.
- \*Remove the power adapter from its power source after use.



PA0198



4 052792 052893

Made in China



\*The specifications and pictures are subject to change without prior notice.  
\*All trade names referenced are the registered trademarks of their respective owners.



## EC-Declaration of Conformity

According to the regulations  
2014/30/EU(EMC) & 2014/35/EU(LVD)  
2009/125/EC(ErP) & 2011/65/EU (RoHS)

### We, Importer / Distributor

2direct GmbH  
Langenstück 5  
58579 Schalksmühle  
Germany

### Declare that the product


Brand Name: **LogiLink**  
Model Number: PA0198  
Switching Power Supply

### Is in Conformity with the following European Standards:

EN 55032:2015  
EN 55035:2017  
EN 61000-3-2:2014  
EN 61000-3-3:2013  
EN 60950-1: 2006+A11:2009+A1:2010+A12:2011+A2:2013  
EN 50581:2012

**Report No: EA1811020E 01001, SA1811020L 01001, UNIA19051303SR-1**

Identification of signatory empowered to bind the manufacturer or his authorized representative.



2direct GmbH  
Langenstück 5

D-58579 Schalksmühle

Tel.: +49-2351-66887-0

Signature: (Wilfried Grobner)

Fax: +49-2351-66887-29

Schalksmühle, 31<sup>st</sup> May 2019

Place and date of issue